



Various access

Be-Tech DMM4 has two access solutions. RF Card key or Mechanical key for your convenience.



Operation status notification

Whenever any operation is made, the LED indicator informs you what is happened through different color and blinking.



Automatic locking

The Be-Tech Digital Door lock automatically locks the door after checking it is properly closed. (Manual operation is also available)



Missing key invalidation

Once you lose your key, it has no validation as long as you re-register rest of your keys.



Emergency power

When the batteries are completely discharged, you can easily supply emergency power to the lock with the standard 9V battery.



Low battery warning signal

A continuous "beep" sound during door access will alert you to replace batteries.



Mechanical key override

For emergency, it can also be unlocked with a mechanical key.



Convenient



Model



Reliable



Safe





Specification

Model	DMM4	Size (W x H x D)	Front body: 78 x 470 x 65 mm : 3.07 x 18.5 x 2.56 inch Back body: 78 x 470 x 65mm : 3.07 x 18.5 x 2.56 inch
RFID	ISO 14443A type (13.56MHz) Capacity: 200 (Included 50 temporary capacity)		
Туре	Mortise Door Handle-Set	Lockset	Mortise (65mm Backset)
Mechanical Key	5 tumbler pin bump proof, 3pcs	Door Thickness	Applicable 45~80mm
Material	Stainless steel	Power	DC 6V (AA Alkaline battery, 4pcs)
Temperature	Workable -20°C ~55°C	Battery Life	Approximately 12 months (Average ~ 10 times per day)
Humidity	Workable 20%~85% non-condensing		



Smart Your Life



Guangdong Be-Tech Security Systems Limited No.17, KeYuan 3 Road, Ronggui

Shunde High-Tech Zone, Foshan, Guangdong 528306, P.R.China Tel:+86 757 28376123 | Fax:+86 757 28308823 E-mail:export@be-tech.com.cn | www.be-tech.com.cn