





Be-Tech Keel II series in-room safe is the valuable choice for hotels with combining fashionable and flat design, which provides high quality and comfort for hotels to secure guest's belongings.

With the attractive design and competitive price, Be-Tech Keel II series safe meets the same security standard and utilizes the same electronic platform as all Be-Tech in-room safes.

FEATURES:

- Fashionable and flat design.
- •ADA compliant telephone-style keypad.
- •4~9 digit guest code.
- •Revolutionary locking system with double deadbolt mechanism.
- •Door-body integrated design for minimum crack between door and body.
- •Integrative solid steel bolt hinges for maximum security and durability.
- •Optional illuminated white keypad.
- LED display for clear visible numbers.
- Powered with 4 AA batteries.
- •Easy external emergence power supply by 9V battery in case batteries fail.
- Easy mechanical key override in case safe fails.
- Spring loaded door.
- •3 size options in body.
- •Laptop compatible up to 17" (for model Keel 5FL).
- •Data synchronization by Smart Button Key(DS1996).
- Inside carpet around body.
- •Optional inside light for guest convenience.
- •Hotel One-Time code usage.
- •Optional internal power outlet options (Universal/ EURO/UK) on inside door for quest convenience.
- Optional AC/DC adapter power supply.



SPECIFICATIONS



Measurements		Keel 10FL	Keel 3FL	Keel 5FL
Outside H/W/D	mm	169/300/230	220/430/350	220/495/350
(Included keypad)	inch	6.65/11.81/9.06	8.66/16.93/13.78	8.66/19.49/13.78
Inside H/W/D	mm	166/297/180	217/427/300	217/487/300
	inch	6.54/11.69/7.09	8.54/16.81/11.81	8.54/19.17/11.81
Door dimensions	mm	115/245	160/370	160/435
H/W	inch	4.53/9.65	6.3/14.57	6,3/17.13
Internal volume	liters	8.87	27.8	31.7
	cu ft	0.31	0.98	1.12
Weight	kg	5.8	12.7	14.1
	Ib	12.79	28	31.09

H/W/D: Height/Width/Depth

•Override: Mechanical key.

•Steel thickness: Door: 5mm / Body: 1.5mm •Fastening method: Backwall: 2 bolts / Bottom: 2 holes

Data Synchronization:

With this function, there is no need for users to setup the safes one by one with keypad. Users just need to setup one of the safe, and synchronize that safe's setting to the sync kit, then programs all of the safes with sync kit. It is fast and convenient solution for programming amount of safes.



External power supply:

When the battery is low, 9V battery with DC external power socket can be used as emergency power supply.



Outlets:

Optional internal power outlet mounted on the inside door available on Keel 3FL and 5FL for guest's convenience of use (Universal, EURO and UK).







AC/DC adapter:

Optional AC/DC adapter power supply for reducing battery consumption. This helps hotels build-up the image of "Green Planet" environmental protection.

Contact us:

Smart Your Life



Guangdong Be-Tech Security Systems Limited No.17, KeYuan 3 Road, Ronggui

Shunde High-Tech Zone, Foshan, Guangdong 528306, P.R.China Tel:+86 757 28376123 | Fax:+86 757 28308823 E-mail:export@be-tech.com.cn | www.betech-security.com